

REV	LOCA	NAME	SUBJECT	DATE
V1.0			初版发行	2017-02-28

Pantone 158C

60%R

100%R

K3C

AC 1900 SMART WI-FI ROUTER

QUICK INSTALLATION GUIDE

Package Contents

The following contents should be found in your box:

- K3C AC1900 Smart Wi-Fi Router
- AC power adapter
- Ethernet cable (RJ-45)
- Quick Installation Guide
- GNU General Public License (GPL)

① Make sure that the package contains the listed items. If any of these above items are damaged or missing, please contact your distributor.

② Keep the original sales receipt and packaging material in case you would need future services such as repair or replacement.

A quick look

Power button Press this button to power on/off the router.

USB 3.0 port Insert USB device as external storage.

WAN (Internet) Connect an Ethernet cable into this port to establish WAN connection.

LAN ports 1-3 and LED Connect Ethernet cables into these ports to establish LAN connection.

Power port Insert the AC adapter connector into this port.

Reset button Press and hold this button for at least 5 seconds until the LED at the bottom edge of the front panel flashes rapidly.

Connecting the devices

① Before you begin, please have your ISP's username and password ready.

② Connect the power adapter into an electrical outlet, connect the other end to the router, and turn on the router.

③ Connect your modem to the WAN port on the router using an Ethernet cable.

④ Make sure your modem has proper Internet connection.

⑤ If you have a wired Ethernet connection to the Internet instead of a modem, connect the Ethernet cable directly to the Internet port on the router, and turn on the router, then continue with the following instructions to complete the router setup.

⑥ Connect your computer to the LAN port on your router with an Ethernet cable.

If you are using a wireless device, turn on Wi-Fi and connect to SSID **PHICOMM_K3C** or **PHICOMM_K3C_XX**. **XX** represents the last two digits of the router's MAC address.

Configuring router via web browser

1. On your web browser, key in **ip:88** or **192.168.2.1** and click **Start Setup** to run the setup wizard.

2. Create a password for your router and click **Next**.

Create a password

Router Password: *****

Re-enter Password: *****

3. Select your time zone and click **Next**.

Time Zone: GMT+08:00 (China)

4. Specify your Internet connection type (contact your Internet service provider about the connection type if you are not sure). Enter your Internet account information as required and click **Next**.

Connection Type: DHCP

Username: *****

Password: *****

5. Set SSID and password for your wireless network or use the default settings. Click **Save** to complete the setup.

SSID: PHICOMM_K3C

Password: *****

6. Click **Save** to complete the setup.

Configuring router via PHICOMM app

To manage your home network with your smartphone, scan the barcode below to download the PHICOMM app from Apple App Store or Google Play.

You can record your router's settings like:

Router password: *****

2.4 GHz SSID: *****

5 GHz SSID: *****

Notification of Compliance

FCC User Information

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

FCC Caution: Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference

to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

FCC Radiation Exposure Statement

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 20cm between the radiator and your body.

PHICOMM (Shanghai) Co., Ltd.
1888 Xiangyin Road, Songjiang District, Shanghai, China
www.phicomm.com

NOTE (技术要求) :

- 成型尺寸 : 130*85mm , 公差 : ±1mm
- 材质 : 128g铜板纸 , 表面过光油
- 折页方式 : M字折
- 印刷颜色 : 除上图标注外, 四色印刷
- 输出网线 : 200 lpi
- 所有原材料和制作工艺均满足RoHS指令、WEEE指令和包装指令 (94/62/EC) 要求。

PHICOMM

Shanghai Feixun Communication Co., Ltd.

TITLE	QIG	UNLESS OTHERWISE SPECIFIED GENERAL TOLERANCE: ≤6 ±0.1 >6-30 ±0.15 >30-120 ±0.20 >120-400 ±0.25 ≥400 ±0.5 ANGULAR ≤ ±1°	MODEL	K3C	UNIT	mm
DRAWING	朱莎莎		DWG NO		SIZE	
CHECKED	郭先鹏		PART NO	811002192	REV	V1.0
APPROVED	杨德军		SCALE	1:1	PAGE OF	1/1