

Wired / Wireless Broadband Router

3G-6200n / 3G-6400n Quick Installation Guide

Version 1.0 / 3, 2009



Multi-Languages QIG on the CD

Český	Českého průvodce rychlou instalací naleznete na přiloženém CD s ovladači.
Deutsch	Auf der beiliegend Treiber CD finden Sie deutsche Anleitung zur Schnellinstallation.
Español	Incluido en el CD el G.R.I. en Español.
Français	Veillez trouver l'français G.I.R ci-joint dans le CD.
Italiano	Incluso nel CD il Q.I.G. in Italiano.
Magyar	A magyar telepítési útmutató megtalálható a mellékelt CD-n.
Nederlands	De nederlandse Q.I.G. treft u aan op de bijgesloten CD
Polski	Skrócona instrukcja instalacji w języku polskim znajduje się na załączonej płycie CD.
Português	Incluído no CD o G.I.R. em Portugues.
Русский	Русский: Найдите Q.I.G. на русском языке на приложенном CD.
Romania	Cd-ul cuprinde Ghid de instalare rapida in limba romana.
Türkçe	Ürün ile beraber gelen CD içinde Türkçe Hızlı Kurulum Kılavuzu'nu bulabilirsiniz.
繁/簡中	CD 片內含繁體中文及簡體中文快速安裝指南

1 Product Introduction	4
1-1 Package Contents.....	5
1-2 Front Panel	5
1-3 Back Panel.....	6
2 Network Setup.....	7
2-1 Hardware Installation:	7
2-2 PC LAN IP Configuration	9
2-3 Internet Configuration	12
2-3-1 Wireless 3G/3.5G Setup.....	12
(A) Plug and play, no setup procedure required.	12
(B) PIN code or user name / password required:.....	12
(C) Driver / Utility required on PC side	15
2-3-2 Router Configuration – PPPoE.....	24
2-3-3 Router Configuration – Dynamic IP.....	26
3 Advanced Setup	28
3-1 Change management password	28
3-2 Firmware Upgrade	29
3-3 Restart and Reset to Default Setting.....	30
3-4 Wireless Setup.....	31

Copyright© by Edimax Technology Co, LTD. all rights reserved. No part of this publication may be reproduced, transmitted, transcribed, stored in a retrieval system, or translated into any language or computer language, in any form or by any means, electronic, mechanical, magnetic, optical, chemical, manual or otherwise, without the prior written permission of this Company .

This company makes no representations or warranties, either expressed or implied, with respect to the contents hereof and specifically disclaims any warranties, merchantability or fitness for any particular purpose. Any software described in this manual is sold or licensed "as is". Should the programs prove defective following their purchase, the buyer (and not this company, its distributor, or its dealer) assumes the entire cost of all necessary servicing, repair, and any incidental or consequential damages resulting from any defect in the software. Further, this company reserves the right to revise this publication and to make changes from time to time in the contents hereof without obligation to notify any person of such revision or changes.

The product you have purchased and the setup screen may appear slightly different from those shown in this QIG. For more detailed information about this product, please refer to the User Manual on the CD-ROM. The software and specifications are subject to change without notice. Please visit our web site www.edimax.com for the update. All rights reserved including all brand and product names mentioned in this manual are trademarks and/or registered trademarks of their respective holders .

Notice according to GNU/GPL-Version 2

This product includes software that is subject to the GNU/GPL-Version 2. You find the text of the license on the product cd/dvd. The program is free software and distributed without any warranty of the author. We offer, valid for at least three years, to give you, for a charge no more than the costs of physically performing source distribution, a complete machine-readable copy of the corresponding source code.

Please contact Edimax at: Edimax Technology co., Ltd, NO. 3, Wu-Chuan 3rd RD
Wu-Ku-Industrial Park, Taipei Hsien, Taiwan. R.O.C., TEL : +886-2-77396888,
FAX : +886-2-77396887, sales@edimax.com.tw

1 Product Introduction

Thank you for purchasing Edimax 3G-6200n / 3G-6400n wireless 3G broadband router! This high cost-efficiency router is the best choice for Mobile / Small office / Home office users, all computers and network devices can share a single wireless 3G modem or xDSL / cable** modem internet connection at high speed. Easy install procedures allows any computer users to setup a network environment in very short time - within minutes, even inexperienced. When the number of your computers and network-enabled devices grow, you can also expand the number of network slot by simple attach a hub or switch, to extend the scope of your network!

You can configure the router by running the Setup Wizard in the CD-ROM provided in the package. The wizard provides quick setup for wireless 3G/3.5G Internet connection, Ethernet WAN Internet connection, SSID, wireless security, firmware upgrade and changing router's password. When you start the Setup Wizard, you will get the following Welcome screen. Please choose the language to start with and follow the easy steps in the Wizard. No instruction for the Setup Wizard is given here.

If you lost the CD-ROM or you prefer the traditional web setup, please follow the procedures in this Quick Installation Guide to configure the router.



Note 1: Only one Internet connection (wireless 3G or xDSL/Cable) can be used at the same time.

Note 2: To prevent the compatibility problem between 3G USB Modem cad and 3G router, it is recommended that you upgrade the latest firmware of 3G router from Edimax website <http://www.edimax.com> .

1-1 Package Contents



Before you starting to use this router, please check if there's anything missing in the package, and contact your dealer of purchase to claim for missing items :

- ☐ 3G Broadband router (main body, 1 pcs)
- ☐ Quick installation guide (1 pcs)
- ☐ One CD-ROM (Including the Setup Wizard, Multi-languages Quick Installation Guide and User Manual)
- ☐ 12V power adapter (1 pcs)
- ☐ Ethernet Cable (1 pcs)
- ☐ Holding Base (1 pcs)
- ☐ Accessories

1-2 Front Panel



3G-6200n / 3G-6400n

LED	Light Status	Description
PWR 	ON	Router is ready
WAN LNK/ACT	ON	WAN is connected
	Off	WAN is unconnected
	Flashing	WAN port is sending / receiving data
LAN LNK/ACT (Port 1-4)	ON	LAN port is connected
	Off	LAN port is unconnected
	Flashing	LAN port is sending / receiving data
3G	ON	3G Modem is connected
	Off	3G Modem is not connected
	Flashing	USB modem card is sending / receiving data
WLAN 	ON	Wireless LAN has been activated
	Off	Wireless LAN is disabled
	Flashing	Wireless LAN is sending / receiving data


1-3 Back Panel



3G-6400n



3G-6200n

Item Name	Description
Power	Power connector, connects to power adapter
Reset / WPS	Reset the router to factory default settings (clear all settings) or start WPS function. (a) Press this button and hold for 20 seconds to clear all settings. (b) Press this button for 2 ~ 5 seconds to start WPS function.
1 – 4	The router's 4 LAN ports are where you connect your LAN's PCs, printer servers, hubs and switches etc.
WAN	Wide Area Network (WAN / Internet) port
USB	For 3G USB Modem Card to connect with Internet
 ON/OFF	You can enable / disable wireless signal (WiFi) via ON/OFF switch button.

2 Network Setup


2-1 Hardware Installation:

Instructions for using the router to share the Internet with multiple PCs. (Power on the Modem and the Router.)


(A) 3G/3.5G Modem card installation:

If you have 3G/3.5G modem card and SIM card, please follow the following instructions to establish connection

1. Connect power adapter to 3G-6200n / 3G-6400n
2. Connect another Ethernet cable from the any LAN ports (1~4) on router to the Ethernet socket on the PC



3. Insert SIM card into 3G/3.5G modem card, and connect the modem card with one of USB port of 3G-6200n / 3G-6400n. The corresponding USB LED indicator on 3G-6200n / 3G-6400n will light.




(B) Cabling installation:

If you do not have 3G USB modem. You can also access Internet by xDSL/Cable modem, please follow the following instructions:


1. Connect the Ethernet cable from the router's WAN port to the LAN port of the modem.

STEP 1.



2. Connect another Ethernet cable from the any LAN ports (1~4) on router to the Ethernet socket on the PC.

STEP 2.



3. Check to make sure the router's LINK LED is lit; to confirm the cable connections are made correctly.


2-2 PC LAN IP Configuration

Configure the PC LAN setting to automatically obtain an IP address from the router by following the below steps.

- Click **“Start”** in the task bar then select the **“Control Panel”**.




- Click **“Switch to Classic View”** on the left top to see more setting icons.




- Find an icon **“Network Connection”** then Double-Click to open the network connection setting.




- You will see an icon **“Local Area Connection”**, select the icon then Right-Click the mouse to open the sub-menu and select the **“Properties”**.



- Select the **“Internet Protocol (TCP/IP)”** then click the **“Properties”**



- Ensure the parameter marked in blue are checked in “**Obtain an IP address automatically**” and “**Obtain DNS server address automatically**” then press “**OK**” to close.



2-3 Internet Configuration

3G-6200n / 3G-6400n provides two types of Internet connection method: wireless (3G/3.5G USB modem) or wired (xDSL / cable modem) connection. You can access internet via USB 3G/3.5G modem card, or via wired xDSL / cable modem connection. However, only one connection method (wireless or wired) can be used at the same time. Related instructions will be given as follow.

2-3-1 Wireless 3G/3.5G Setup

3G-6200n / 3G-6400n supports most of 3G/3.5G modem cards, just connect the modem card to the USB port of 3G-6200n / 3G-6400n and 3G-6200n / 3G-6400n will recognize it automatically, no additional setup procedure required. However, some of modem cards require PIN code or account / password (you have to use 3G-6200n / 3G-6400n's web interface to input these information), and some modem cards requires you to connect the modem card with your PC and install driver / utility before you connect it with 3G-6200n / 3G-6400n (all PCs which need to access Internet by 3G-6200n / 3G-6400n requires to perform this procedure once). If you still not able to connect to Internet, please use wired Internet connection to access our website :<http://www.edimax.com/> ,download latest version of firmware and upgrade 3G-6200n / 3G-6400n's firmware. If you still not be able to get connected by your 3G/3.5G modem card, please contact your dealer of purchase and provide the model name of the 3G/3.5G modem card you have, we'll try our best to help you to solve the problem.

Only one Internet connection (wireless / wired) can be used at the same time. Wireless connection (3G/3.5G) will be selected first, and use wired Internet connection as backup. Therefore, please DO NOT connect your 3G/3.5G modem card with 3G-6200n / 3G-6400n, or your telecomm service provider may charge you with high communication fee. For example, if you connect 3G/3.5G modem card with 3G-6200n / 3G-6400n when you're using wired Internet connection, wired connection will be dropped and use 3G/3.5G wireless connection instead. If 3G/3.5G wireless signal reception is poor and the connection can not be restored within 60 seconds, 3G-6200n / 3G-6400n will use wired Internet connection again, and will not switch back to wireless Internet connection (This only happens with wired Internet connection is available. If wired connection is unavailable, 3G-6200n / 3G-6400n will try to establish 3G/3.5G wireless connection again and again). If you want to use 3G/3.5G wireless connection again, you need to remove 3G/3.5G modem card from 3G-6200n / 3G-6400n and reconnect it back after 5 seconds.


(A) Plug and play, no setup procedure required.

Connect the USB 3G/3.5G modem card with 3G-6200n / 3G-6400n and make sure the corresponding USB LED indicator of 3G-6200n / 3G-6400n lights up, then you

can use the web browser to access Internet.

(B) PIN code or user name / password required:

If you still can't access Internet, please enter the router's default IP address: **"192.168.2.1"** into your PC's web browser and press **"enter"**




The login screen below will appear. Enter the "User Name" and "Password" and click **"OK"** to login. The default User name is **"admin"** and Password is **"1234"**,

If following window does not appear, please make sure you finished 'PC LAN IP Configuration' as described in chapter 2-2, and then try again.



The main page will appear, click **“Quick Setup”** to setup the Internet connection.



Select '(GMT) Greenwich Mean Time: (your country or city)' then Click **“Next”** button.



Please check the authentication method you want to use. Most of telecomm service providers require you to input PIN Code, please input the PIN code provided by telecomm service provider. Most of options listed here are optional and you don't have to provide those information if telecomm service provider doesn't provide you with those information.

If telecomm provider provides you with username / password, please check /User Name / Password box and input the user name / password provided by telecomm service provider, then click ' OK ' button. Wait for 1 minute (for 3G-6200n / 3G-6400n to reboot), then you can access Internet.



Please input User name & Password in “PPP Settings” and do not input them in “Network Settings” unless your ISP ask you input them in both.

PPP Settings :

Username :	<input type="text"/>
Password :	<input type="password"/>
Idle Timeout :	<input type="text" value="0"/>
Echo Timeout :	<input type="text" value="60"/>
Echo Count :	<input type="text" value="3"/>

Network Settings :

User Name	<input type="text"/>	(Optional)
Password	<input type="password"/>	(Optional)
Enter PIN Code	<input type="text"/>	
APN	<input type="text" value="internet"/>	
Service	3G/3.5G Only (UMTS/HSPA/HSDPA) ▼	

Note: Please choose “CDMA”, if your ISP use 3G CDMA system.

Service	CDMA ▼
---------	--------

(C) Driver / Utility required on PC side

Some 3G/3.5G modem card does not work with instructions (A) or (B) listed above (ex. BandLuxe C100S). You need to install 3G/3.5G modem card driver / utility on

every PC which needs to access Internet first. After driver / utility installation is complete, every PC will be able to access Internet via 3G/6200n / 3G-6400n.


1. Plug in the BandLuxe C100S modem card to the USB port of your computer.
2. The system will detect the hardware of C100S USB adapter and also the storage inside the adapter.




3. Please click "Cancel" to ignore the message of the found new hardware wizard.




4. Please go to “My computer”, you will see the BandLuxe C100S. Double click the device.




5. The program inside the adapter will prepare to install the driver and utility of the adapter.




6. Click “Next”.




7. Select “I accept the terms in the license agreement” and click “Next”.




8. If you want to change the destination folder, please click “Change”. Click “Next” to continue.




9. Click “install”.



10. The system is installing the driver and utility of the adapter.



11. Install successfully, click “Finish” to close the install wizard.



12. The utility of C100S will start up automaticity.
Please select the “MENU”




13. Click “Setting”.



14. Select the “Auto connect on startup”.



15. Plug in the C100S into the USB port of the 3G router.
16. The USB adapter will get the IP address from ISP automatically. You can check the Status of the 3G-6200n / 3G-6400n on the Web site (ex: 192.168.2.1).



The screenshot shows the EDIMAX web interface with the 'Internet Connection' status page. The left sidebar contains a navigation menu with 'Status' selected, and a 'Current Time' display showing 3/9/2009 5:39:00. The main content area displays the current internet connection status and related information.

Attain IP Protocol :	Dynamic IP disconnect
IP address :	
Subnet Mask :	
Default Gateway :	10.64.64.68
MAC address :	00:0E:2E:44:69:CA
Primary DNS :	210.241.192.201
Secondary DNS :	168.95.1.1
WWAN Status:	Connected
IP Address:	118.231.54.74
Subnet Mask:	255.255.255.255
Gateway:	10.64.64.68
Manufacturer:	BandRich, Inc. (0x1a8d)
Product:	BandLuxe 3.5G HSDPA Adapter (0x1002)
IMEI:	355776010450878

17. Now you are able to connect to Internet successfully.




Note : If your SIM card requires entering the PIN code, please enter into the web management of the 3G router. In WAN setting web page, select 3G/3.5G. Enter the PIN code of the adapter.

PPP Settings :

Username :	<input type="text"/>
Password :	<input type="password"/>
Idle Timeout :	<input type="text" value="0"/>
Echo Timeout :	<input type="text" value="60"/>
Echo Count :	<input type="text" value="3"/>

Network Settings :


User Name	<input type="text"/>	(Optional)
Password	<input type="password"/>	(Optional)
Enter PIN Code	<input type="text"/>	
APN	<input type="text" value="internet"/>	
Service	<input type="text" value="CDMA"/>	

2-3-2 Router Configuration – PPPoE

Note: Please do not run the PPPoE software; otherwise the Internet connection for the router may fail.

The following instruction will help you to get connected if you have xDSL / cable Internet connection

Please enter the router's default IP address: “**192.168.2.1**” into your PC's web browser and press “**enter**”



The login screen below will appear. Enter the “User Name” and “Password” and click “**OK**” to login. The default User name is “**admin**” and Password is “**1234**”,



1. Select “PPPoE xDSL”, the system will move into next step

Quick Setup | General Setup | Status Info | System Tools

1. Time Zone
2. WAN Type
3. IP Address Info

☐ **3G/3.5G**
If you connect to Internet using an 3G/3.5G handset or 3G/3.5G USB modem, then you should choose this option and enter the required information.

☐ **Cable Modem**
A connection through a cable modem requires minimal configuration. When you set up an account with your Cable provider, the Cable provider and your Wireless Router will automatically establish a connection, so you probably do not need to enter anything more.

☐ **Fixed-IP xDSL**
Some xDSL Internet Service Providers may assign a Fixed IP Address for your Wireless Router. If you have been provided with this information, choose this option and enter the assigned IP Address, Subnet Mask, Gateway IP Address and DNS IP Address for your Wireless Router.

☐ **PPPoE xDSL**
If you connect to the Internet using an xDSL Modem and your ISP has provided you with a Password and a Service Name, then your ISP uses PPPoE to establish a connection. You must choose this option and enter the required information.

2. Enter the “User Name” and “Password” that ISP provided and leave the others. (The “Service Name” can be blank) and click “OK” to save the setting then reboot the router

PPPoE


Enter the User Name and Password required by your ISP in the appropriate fields. If your ISP has provided you with a “Service Name” enter it in the Service Name field, otherwise, leave it blank.

User Name :	<input type="text"/>
Password :	<input type="password"/>
Service Name :	<input type="text"/>
MTU :	<input type="text" value="1392"/> (512<=MTU<=1492)
Connection Type :	<input type="text" value="Continuous"/> <input type="button" value="Connect"/> <input type="button" value="Disconnect"/>
Idle Time Out :	<input type="text" value="10"/> (1-1000 Minute)

3. After reboot, your router is now ready for Internet connection.

2-3-3 Router Configuration – DHCP(Dynamic IP or Cable Modem)


Please enter the router's default IP address: “**192.168.2.1**” into your PC's web browser and press “**enter**”



The login screen below will appear. Enter the “User Name” and “Password” and click “**OK**” to login. The default User name is “**admin**” and Password is “**1234**”,



1. Select “**Cable Modem**”, the system will move into next step



Quick Setup | General Setup | Status Info | System Tools

1. Time Zone
2. WAN Type
3. IP Address Info


☐ **3G/3.5G**
If you connect to Internet using an 3G/3.5G handset or 3G/3.5G USB modem, then you should choose this option and enter the required information.

☒ **Cable Modem**
A connection through a cable modem requires minimal configuration. When you set up an account with your Cable provider, the Cable provider and your Wireless Router will automatically establish a connection, so you probably do not need to enter anything more.

☐ **Fixed-IP xDSL**
Some xDSL Internet Service Providers may assign a Fixed IP Address for your Wireless Router. If you have been provided with this information, choose this option and enter the assigned IP Address, Subnet Mask, Gateway IP Address and DNS IP Address for your Wireless Router.

☐ **PPPoE xDSL**
If you connect to the Internet using an xDSL Modem and your ISP has provided you with a Password and a Service Name, then your ISP uses PPPoE to establish a connection. You must choose this option and enter the required information.

2. Enter “**Host Name**” and “**MAC Address**”. (The “**Host Name**” can be blank)
The MAC Address is provided by ISP (e.g. NTL) or click “**Clone Mac Address**” button if you’re using the computer’s MAC Address.
Confirm with your ISP about MAC Address used, Click “**OK**” button to save the settings then reboot the router.



Dynamic IP

Cable Modem

Host Name :

MAC Address :

3. After reboot, your router is now ready for Internet connection.

Note: Check the manual on the CD for more Internet connection type and other setting details


3 Advanced Setup

3-1 Change management password

Default password of this router is 1234, and it's displayed on the login prompt when accessed from web browser. There's a security risk if you don't change the default password, since everyone can see it.

To change password, please follow the following instructions:

Please click 'System' menu on the left of web management interface, then click 'Password Settings', and the following message will be displayed on your web browser:



The screenshot shows the router's web management interface. At the top, there are tabs: 'Quick Setup', 'General Setup', 'Status Info', and 'System Tools'. On the left side, there is a 'System' menu with sub-items: 'Time Zone', 'Password Settings' (highlighted with a red box), and 'Remote Management'. Below these are other system settings like '3G/3.5G', 'WAN', 'LAN', 'Wireless', 'QoS', 'NAT', and 'Firewall'. The main content area is titled 'Password Settings' and contains a text box explaining that the default password is 1234 and that passwords can be 0 to 30 alphanumeric characters long. Below this text are three input fields labeled 'Current Password', 'New Password', and 'Confirm Password'. At the bottom right of the form are 'APPLY' and 'CANCEL' buttons.

Here are descriptions of every setup items:

Current Password:	Please input current password here.
New Password :	Please input new password here.
Confirmed Password :	Please input new password here again.

When you finish, click 'Apply'; If you want to keep original password unchanged, click 'Cancel'.

3-2 Firmware Upgrade

The system software used by this router is called as 'firmware', just like any applications on your computer, when you replace the old application with a new one, your computer will be equipped with new function. You can also use this firmware upgrade function to add new functions to your router, even fix the bugs of this router.

To upgrade firmware, please follow the following instructions:

Please click 'System Tool' located at the upper-right corner of web management interface, then click 'Firmware Upgrade' on the left of web management interface, then the following message will be displayed on your web browser:



Please click 'Next', and the following message will be displayed:



Click 'Browse' button first, you'll be prompted to provide the filename of firmware upgrade file. Please download the latest firmware file from our website, and use it to upgrade your router.

After a firmware upgrade file is selected, click 'Apply' button, and the router will start

firmware upgrade procedure automatically. The procedure may take several minutes, please be patient.


NOTE: Never interrupt the upgrade procedure by closing the web browser or physically disconnect your computer from router. If the firmware you uploaded is corrupt, the firmware upgrade will fail, and you may have to return this router to the dealer of purchase to ask for help. (Warranty voids if you interrupted the upgrade procedure).

3-3 Restart and Reset to Default Setting

If you found the router behaves strangely, you can perform a reset, sometimes it will solve the problem.

You can either reset your router without losing your current settings or restore to factory defaults. If you wish to reset the router to the factory default settings, select “Factory Default Settings” then click “Restart”.

Alternatively, you can use the Reset button at the Real Panel of the router.



Please click ‘Apply’ to reset your router, and it will be available again after few minutes, please be patient.

3-4 Wireless Setup

SSID is the name of the wireless router. You may change your SSID to a meaningful name so that you can identify your wireless router from others. You can use any alphanumeric characters, up to 32 characters. By default the ESSID is 'default'.

It's very important to set wireless security settings properly! If you don't, hackers and malicious users can reach your network and valuable data without your consent and this will cause serious security problem.

To secure your wireless network, please click "Interface Setup", then click "Wireless", and follow the following instructions to configure the wireless security settings:

It's recommended to use WPA to protect your wireless router from hackers. Select Enabled WPA-PSK and enter the Pre-Share Key below.

Use 8-32 alphanumeric characters. Please remember this key, you need this key to connect to your wireless router wirelessly.

The screenshot shows the EDIMAX web interface for configuring wireless security. The left sidebar has a menu with 'Security Settings' highlighted. The main content area is titled 'Security Settings' and includes a description: 'This page allows you setup the wireless security. Turn on WEP or WPA by using Encryption Keys could prevent any unauthorized access to your wireless network.' Below this is a table with the following settings:

Encryption :	WPA pre-shared key
WPA Unicast Cipher Suite :	<input checked="" type="radio"/> WPA(TKIP) <input type="radio"/> WPA2(AES) <input type="radio"/> WPA2 Mixed
Pre-shared Key Format :	Passphrase
Pre-shared Key :	*****

At the bottom right of the table are two buttons: 'APPLY' and 'CANCEL'.

Note: Please refer to the User Manual in the CD-ROM for more details information on Internet connection type and to configure all others setting.

Federal Communication Commission Interference Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

1. Reorient or relocate the receiving antenna.
2. Increase the separation between the equipment and receiver.
3. Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
4. Consult the dealer or an experienced radio technician for help.

FCC Caution

This device and its antenna must not be co-located or operating in conjunction with any other antenna or transmitter.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Any changes or modifications not expressly approved by the party responsible for compliance could void the authority to operate equipment.

Federal Communications Commission (FCC) Radiation Exposure Statement

This equipment complies with FCC radiation exposure set forth for an uncontrolled environment. In order to avoid the possibility of exceeding the FCC radio frequency exposure limits, human proximity to the antenna shall not be less than 2.5cm (1 inch) during normal operation.

Federal Communications Commission (FCC) RF Exposure Requirements

SAR compliance has been established in the laptop computer(s) configurations with PCMCIA slot on the side near the center, as tested in the application for Certification, and can be used in laptop computer(s) with substantially similar physical dimensions, construction, and electrical and RF characteristics. Use in other devices such a PDAs or lappads is not authorized.

This transmitter is restricted for use with the specific antenna tested in the application for Certification. The antenna(s) used for this transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

R&TTE Compliance Statement

This equipment complies with all the requirements of DIRECTIVE 1999/5/EC OF THE EUROPEAN PARLIAMENT AND THE COUNCIL of March 9, 1999 on radio equipment and telecommunication terminal Equipment and the mutual recognition of their conformity (R&TTE)

The R&TTE Directive repeals and replaces in the directive 98/13/EEC (Telecommunications Terminal Equipment and Satellite Earth Station Equipment) As of April 8, 2000.

Safety

This equipment is designed with the utmost care for the safety of those who install and use it. However, special attention must be paid to the dangers of electric shock and static electricity when working with electrical equipment. All guidelines of this and of the computer manufacture must therefore be allowed at all times to ensure the safe use of the equipment.

EU Countries Intended for Use

The ETSI version of this device is intended for home and office use in Austria, Belgium, Denmark, Finland, France, Germany, Greece, Ireland, Italy, Luxembourg, Bulgaria, Cyprus, Czech Republic, Estonia, Hungary, Latvia, Lithuania, Malta, Poland, Romania, Slovakia, Slovenia, the Netherlands, Portugal, Spain, Sweden, and the United Kingdom.

The ETSI version of this device is also authorized for use in EFTA member states: Iceland, Liechtenstein, Norway, and Switzerland.

EU Countries not intended for use

None

A declaration of conformity is available on www.edimax.com





EDIMAX Technology Co., Ltd.

www.edimax.com