

**D-Link®**

WIRELESS G ADSL2+ ROUTER  
DSL-2640BT

คู่มือการติดตั้งเบื้องต้น

QUICK INSTALLATION GUIDE


# CONTENTS OF PACKAGING

## CONTENTS



### **INSTALLATION CD**

INCLUDES SET-UP WIZARD & TECHNICAL MANUALS



### **WIRELESS G ADSL2+ ROUTER**

DSL-2640BT



### **POWER ADAPTER**

ADAPTER



### **ETHERNET CABLE (CAT5 UTP)**

CONNECT THE ROUTER TO YOUR PC DURING SET-UP



### **RJ-11 PHONE CABLE**



If any of these items are missing from your packaging contact your reseller

# PRODUCT SETUP

## CD SETUP WIZARD



### SET-UP WIZARD CD

The CD contains all of the instructions required to set-up DSL-2640BT



### INSERT CD

Insert the CD into the CD drive of your computer. The set-up wizard should start automatically. Make sure that your internet connection is active. (Do not plug in DSL-2640BT yet)



### SET-UP WIZARD

Select your language from the list of options and follow the steps within the wizard to complete the set-up of DSL-2640BT

## ADVANCED SET-UP [ACCESS VIA IP ADDRESS]

To configure DSL-2640BT manually (without the set-up CD) connect your computer to the DSL-2640BT using the ethernet cable provided. Then connect the power cable on the DSL-2640BT. The power light will display as solid blue.

Then simply open a browser window and enter the IP address in the browser address field:

IP ADDRESS: <http://192.168.1.1>

USERNAME: admin

PASSWORD: admin

# TROUBLESHOOTING

## SET-UP AND CONFIGURATION PROBLEMS

### 1. HOW DO I CONFIGURE MY DSL-2640BT ROUTER WITHOUT THE CD, OR CHECK MY WIRELESS NETWORK NAME (SSID) AND WIRELESS ENCRYPTION KEY?

- Connect your PC to the router using an Ethernet cable.
- Open a web browser and enter the address <http://192.168.1.1>
- The default username is "admin". The default password is "admin".
- If you have changed the password and can not remember it, you will need to reset the router to set the password back to "admin".

### 2. HOW DO I RESET MY DSL-2640BT ROUTER TO FACTORY DEFAULT SETTINGS?

- Ensure the router is powered on.
  - Press and hold the reset button on the rear of the device for 20 seconds.
- Note: Resetting the router to factory default will erase the current configuration settings. To re-configure your settings, log into the router as outlined in question 1, then run the Setup Wizard.

### 3. HOW DO I ADD A NEW WIRELESS CLIENT OR PC IF I HAVE FORGOTTEN MY WIRELESS NETWORK NAME (SSID) OR WIRELESS ENCRYPTION KEY?

- Every PC that needs to connect to the router wirelessly, you will need to ensure you use the correct Wireless Network Name (SSID) and encryption key.
- Use the web based user interface (as described in question 1 above) to check or choose your wireless settings.
- Make sure you write down these settings so that you can enter them into each wirelessly connected PC. You will find a dedicated area on the back of this document, this important information for future use.

### 4. WHY CAN I NOT GET AN INTERNET CONNECTION?

- For Cable users make sure Clone MAC address option is ticked during Wizard installation (or enter the registered MAC) and make sure the service has been enabled/connected and is operational.
- For ADSL users please contact your ISP to make sure the service has been enabled/connected by your ISP and that your ISP username and password is correct.

You can find software updates and user documentation on the D-Link website.

## Tech Support for customers in

### Australia:

Tel: 1300-766-868  
24/7 Technical Support  
Web: <http://www.dlink.com.au>  
E-mail: [support@dlink.com.au](mailto:support@dlink.com.au)

### India:

Tel: 1800-233-0000 (MTNL & BSNL Toll Free)  
+91-832-2885700 (GSM, CDMS & Others)  
Web: [www.dlink.co.in](http://www.dlink.co.in)  
E-Mail: [helpdesk@dlink.co.in](mailto:helpdesk@dlink.co.in)  
[techsupport@dlink.co.in](mailto:techsupport@dlink.co.in)

### Indonesia, Malaysia, Singapore and Thailand:

Tel: +62-21-5731610 (Indonesia)  
Tel: 1800-882-880 (Malaysia)  
Tel: +65 6501 4200 (Singapore)  
Tel: +66-2-719-8978/9 (Thailand)  
24/7, for English Support only  
Web: <http://www.dlink.com.sg/support/>  
E-mail: [support@dlink.com.sg](mailto:support@dlink.com.sg)

### Korea:

Tel: +82-2-2028-1815  
Monday to Friday 9:00am to 6:00pm  
Web: <http://www.d-link.co.kr>  
E-mail: [arthur@d-link.co.kr](mailto:arthur@d-link.co.kr)

### New Zealand:

Tel: 0800-900-900  
24/7 Technical Support  
Web: <http://www.dlink.co.nz>  
E-mail: [support@dlink.co.nz](mailto:support@dlink.co.nz)

### Egypt:

Tel: +202-2919035  
+202-2919047  
Sunday to Thursday 9:00am to 5:00pm  
Web: <http://support.dlink-me.com>  
E-mail: [support.eg@dlink-me.com](mailto:support.eg@dlink-me.com)

### Iran:

Tel: +98-21-88880918,19  
Saturday to Thursday 9:00am to 5:00pm  
Web: <http://support.dlink-me.com>  
E-mail: [support.ir@dlink-me.com](mailto:support.ir@dlink-me.com)  
[support@dlink.ir](mailto:support@dlink.ir)

## TECHNICAL SUPPORT

You can find software updates and user documentation on the D-Link website.

**Tech Support for customers in****Israel:**

Magshimim 20, Petach Tikva 49348  
Main Tel: 972-3-9215173  
Customer Support Tel: 972-3-9212886  
Web: [www.dlink.co.il](http://www.dlink.co.il)

**Pakistan:**

Tel: +92-21-4548158  
+92-21-4548310  
Monday to Friday 10:00am to 6:00pm  
Web: <http://support.dlink-me.com>  
E-mail: [zkashif@dlink-me.com](mailto:zkashif@dlink-me.com)

**South Africa and Sub Sahara Region:**

Tel: +27-12-665-2165  
08600 DLINK (for South Africa only)  
Monday to Friday 8:30am to 9:00pm South Africa Time  
Web: <http://www.d-link.co.za>  
E-mail: [support@d-link.co.za](mailto:support@d-link.co.za)

**Turkey:**

Tel: +90-212-2895659  
Monday to Friday 9:00am to 6:00pm  
Web: <http://www.dlink.com.tr>  
E-mail: [turkiye@dlink-me.com](mailto:turkiye@dlink-me.com)

**U.A.E and North Africa:**

Tel: +971-4-4278127 (U.A.E)  
Sunday to Thursday 9.00AM to 6.00PM GMT+4  
Web: <http://www.dlink-me.com>  
E-mail: [support.me@dlink-me.com](mailto:support.me@dlink-me.com)

**Saudi ARABIA (KSA):**


Tel: +971-4-4278127 (U.A.E)  
Sunday to Thursday 9.00AM to 6.00PM GMT+4  
Web: <http://www.dlink-me.com>  
E-mail: [support.me@dlink-me.com](mailto:support.me@dlink-me.com)

# รายการของอุปกรณ์ในบรรจุภัณฑ์

## รายละเอียด



แผ่น CD ช่วยในการติดตั้ง  
ประกอบด้วย SET-UP WIZARD และ คู่มือทางเทคนิค



อุปกรณ์ WIRELESS G ADSL2+ ROUTER  
รุ่น DSL-2640BT



ปลั๊กจ่ายไฟ อแดปเตอร์  
อแดปเตอร์



**ETHERNET CABLE (CAT5 UTP)**  
CONNECT THE ROUTER TO YOUR PC DURING SET-UP



สายสัญญาณโทรศัพท์ แบบ RJ-11



ถ้าหากตรวจพบว่าอุปกรณ์ขาดหายไปในการบรรจุภัณฑ์ กรุณาติดต่อกับร้าน  
ค้าที่ท่านได้ซื้อมา

# การติดตั้งอุปกรณ์เบื้องต้น

โดยการใช้แผ่น CD SETUP WIZARD

THAI



## แผ่น SET-UP WIZARD CD

ในแผ่น CD ประกอบด้วยขั้นตอนที่ใช้ในการติดตั้ง DSL-2640BT



## ใส่แผ่น CD เพื่อติดตั้ง

ใส่แผ่น CD ลงในไดรฟ์ CD ของเครื่องคอมพิวเตอร์ของคุณ โปรแกรม set-up wizard จะเปิดขึ้นมาอัตโนมัติ กรุณาเช็คเพื่อให้แน่ใจว่าการเชื่อมต่ออินเทอร์เน็ตใช้งานได้ (ยังไม่ต้อง ทำการเชื่อมต่อไปที่ตัว DSL-2640BT)



## โปรแกรม SET-UP WIZARD

เลือกภาษาที่ใช้ทำการติดตั้งจากรายการ และทำตามขั้นตอนในโปรแกรมจนครบทุกขั้นตอนการติดตั้ง DSL-2640BT

## การติดตั้งขั้นสูง (โดยผ่านทาง IP ADDRESS)

ในการติดตั้ง DSL-2640BT แบบด้วยตัวเอง (ไม่ใช่แผ่น set-up CD) ให้เชื่อมต่อคอมพิวเตอร์ของคุณไปที่ DSL-2640BT โดยใช้สายแลน จากนั้นต่อสายจ่ายไฟเข้ากับ DSL-2640BT ไฟแสดงสถานะการณทำงานจะติดค้างเป็นสีฟ้า

ต่อจากนั้นให้เปิดโปรแกรมบราวเซอร์ และใส่ IP Address ลงในช่อง address:

IP ADDRESS: <http://192.168.1.1>

USERNAME: admin

PASSWORD: admin



# การแก้ปัญหาเบื้องต้น

## ปัญหาในการติดตั้งและการกำหนดค่าต่างๆ

1. จะต้องทำอะไรในการกำหนดค่าของ DSL-2640BT โดยไม่ใช้แผ่น CD, หรือถ้าต้องการตรวจสอบ ชื่อของไวร์เลส (SSID) และรหัสการป้องกันการใช้งานไวร์เลส?
  - เชื่อมต่อเครื่องคอมพิวเตอร์เข้าไปที่ตัวเราท์เตอร์โดยใช้สายแลน
  - เปิดโปรแกรมเว็บเบราว์เซอร์ขึ้นมาแล้วพิมพ์ <http://192.168.1.1>
  - ค่าเริ่มต้นของ username คือ "admin" และ password คือ "admin"
  - ถ้าคุณสามารถทำการเปลี่ยน password และไม่สามารถจำค่าได้, จะต้องทำการรีเซ็ตตัวเราท์เตอร์เพื่อให้ค่า password กลับไปที่ "admin"
2. จะทำอย่างไรถ้าต้องการรีเซ็ต DSL-2640BT ให้กลับไปค่าเริ่มต้นที่ติดตั้งมากจากโรงงาน?
  - ตรวจสอบให้แน่ใจว่าเราท์เตอร์เปิดอยู่
  - กดปุ่มรีเซ็ตที่อยู่ด้านหลังของตัวอุปกรณ์ค้างไว้ประมาณ 20 วินาที

หมายเหตุ: การรีเซ็ตเราท์เตอร์ให้กลับไปค่าเริ่มต้นที่มาจากโรงงานจะลบค่าปัจจุบันที่ถูกกำหนดไว้ในการกลับมากำหนดค่าอีกครั้ง ให้ทำการ log-in ตามวิธีในปัญหาข้อที่ 1 แล้วทำการใช้งาน Setup Wizard.
3. จะต้องทำอะไรถ้าต้องการติดตั้งไวร์เลสตัวลูกข่าย หรือในคอมพิวเตอร์ถ้ามีชื่อของตัวปล่อยสัญญาณไวร์เลส (SSID) หรือรหัสการป้องกันการใช้งานไวร์เลส?
  - คอมพิวเตอร์ทุกเครื่องจะต้องเชื่อมต่อกับเราท์เตอร์ผ่านไวร์เลส, คุณต้องแน่ใจว่าคุณได้ใส่ชื่อของตัวปล่อยสัญญาณไวร์เลส (SSID) และรหัสการเข้าใช้งานถูกต้อง
  - ให้ใช้หน้าเว็บของผูู้ใช้งาน (จากที่ได้อีกแล้วไว้ในข้อที่ 1) เพื่อตรวจสอบหรือเลือกการกำหนดค่าไวร์เลสของคุณเอง
  - คุณต้องแน่ใจว่าได้ทำการการติดตั้งที่ได้กล่าวมาแล้วซึ่งจะทำให้คุณสามารถเชื่อมต่อไวร์เลสจากเครื่องคอมพิวเตอร์ของคุณได้ คุณจะพบช่องที่ใหญ่คุณใส่เพื่ออ้างอิงไดตามหลังของคุณคือ ซึ่งจะมี ความสำคัญในการใช้งานในอนาคต
4. เพราะเหตุใดจึงไม่สามารถเชื่อมต่ออินเทอร์เน็ตได้?
  - สำหรับผู้ใช้เคเบิลโมเด็ม ตรวจสอบให้แน่ใจว่าตัวเลือก Clone MAC address ถูกเลือกอยู่ในขณะที่ใช้การติดตั้งแบบ Wizard (หรือใส่ค่า MAC ที่ถูกลงทะเบียนไว้) และต้องแน่ใจว่าการให้บริการบนไฟโตหรือเชื่อมต่ออยู่
  - สำหรับผูู้ใช้งาน ADSL กรุณาติดต่อไปที่ผู้ให้บริการเพื่อตรวจสอบว่าเปิดให้บริการหรือเชื่อมต่ออยู่ โดยผู้ให้บริการและความถูกต้องของ username และ password ของผู้ให้บริการ

## ความช่วยเหลือทางเทคนิค

คุณสามารถค้นหาโปรแกรมที่ได้รับการปรับปรุงใหม่และเอกสารของผู้ใช้งานได้ทางเว็บไซต์  
[www.dlink.co.th](http://www.dlink.co.th)

### การบริการทางเทคนิคสำหรับลูกค้าใน

### อินโดนีเซีย, มาเลเซีย, สิงคโปร์ และไทย:

|                       |             |
|-----------------------|-------------|
| Tel: +62-21-5731610   | (Indonesia) |
| Tel: 1800-882-880     | (Malaysia)  |
| Tel: +65 6501 4200    | (Singapore) |
| Tel: +66-2-719-8978/9 | (Thailand)  |

24/7, for English Support only  
Web: <http://www.dlink.com.sg/support/>  
E-mail: [support@dlink.com.sg](mailto:support@dlink.com.sg)

## NOTES

# WIRELESS NETWORK REMINDER

Wireless Network Name (SSID)

Wireless Network Password